


# 1000W MODIFIED SINE WAVE DC TO AC POWER INVERTER



Model	CAR1K-121	CAR1K-122	CAR1K-241	CAR1K-242	CAR1K-481	CAR1K-482
Rated power	1000W					
Surge power	2000W(Few seconds)					
Output voltage	110V	230V	110V	230V	110V	230V
Output frequency	50/60Hz ± 3					
No load current draw	≤ 0.8A					
Output waveform	Modified Sine Wave 					
USB port	5V, 500mA/2.1A(Optional)				For 48V input, No USB	
Protection function	Bat. low voltage alarm & shut down, over temperature, over voltage, short circuit, reverse polarity, earth leakage, overload					
Input voltage	12V		24V		48V	
Replaceable fuse	30A × 4		15A × 4		7.5A × 4	
Cooling fan	By load control					
Remote control	Optional					
Dimension	27.5 x 20.5 x 7.8cm (L x W x H)					
N.W./Unit	2480g					
QTY/Ctn	6pcs					
Meas./Ctn	50 x 33 x 44.5cm					
Packing	Gift box					
Certification	CE-EMC/LVD, RoHS, E-mark					



» Socket detail please see page 52



فروشگاه اروین سولار

تلفن: ۰۲۱ - ۳۳۹۹۹۰۵۶  
همت بلند ۰۲۱ - ۳۳۹۹۹۰۷۲

www.ervinsolar.ir  
ervinsolar@hotmail.com