


1600W MODIFIED SINE WAVE DC TO AC POWER INVERTER



Model	CAR1.6K-121	CAR1.6K-122	CAR1.6K-241	CAR1.6K-242	CAR1.6K-481	CAR1.6K-482
Rated power	1600W					
Surge power	3200W(Few seconds)					
Output voltage	110V	230V	110V	230V	110V	230V
Output frequency	50/60Hz ± 3					
No load current draw	≤ 1A					
Output waveform	Modified Sine Wave 					
USB port	5V, 500mA/2.1A(Optional)				For 48V input, No USB	
Protection function	Bat. low voltage alarm & shut down, over temperature, over voltage, short circuit, reverse polarity, earth leakage, overload					
Input voltage	12V		24V		48V	
Replaceable fuse	40A × 5		20A × 5		10A × 5	
Cooling fan	By load control					
Remote control	Optional					
Dimension	32.5 x 20.8 x 7.7cm(L x W x H)					
N.W./Unit	3200g					
QTY/Ctn	4pcs					
Meas./Ctn	51.5 x 39 x 31.5cm					
Packing	Gift box					
Certification	CE-EMC/LVD, RoHS, E-mark					



» Socket detail please see page 52



فروشگاه اروین سولار

تلفن: ۰۲۱ - ۳۳۹۹۹۰۵۶
همت بلند ۰۲۱ - ۳۳۹۹۹۰۷۲

www.ervinsolar.ir
ervinsolar@hotmail.com