



فروشگاه اروین سولار
تلفن : ۰۲۱-۳۳۹۹۹۰۵۶
هت بلند : ۰۲۱-۳۳۹۹۹۰۷۲
www.ervinsolar.ir
ervinsolar@hotmail.com

carsPA
ENERGY



Product Features:

- Softstart function
 - Average self-consumption when switched off 0 Watt
 - Reverse polarity protection for battery (fuse trips)
 - Automatic shutdown in case of overload or short circuit
 - Approved for operation in the vehicle
 - Sturdy housing made of aluminum and sheet metal
 - Certificates: Converters, CE, RoHS; E8 Production according to DIN ISO 9001: 2000.
- Tip: Not suitable for coffee pod coffee machines, you need a pure sine wave power inverter

Specifications:

Model	CAR3KU	
Output waveform	Modified Sine Wave	
Rated power	3000W	
Surge power	6000W	
Output voltage	110V/230V(alternative)	
Output frequency	50/60Hz±3(alternative)	
Input voltage	12V/24V/48V(alternative)	
USB port	5V 500mA/2.1A(alternative)	For 48V input, no USB
Remote control	Optional	
Certification	CE-EMC/LVD, RoHS	
Warranty	18 months	
Dimension	42*23*10.8cm (L*W*H)	
N.W/unit	7450g	
Packing	Gift box; 2pcs/15.8Kgs/CTN; 49×31.5×38.5cm	
Packing list	1 * 3000W Power Inverter; 1 * User Manual; Spare fuse; DC connect cable*1 set	