



• **Product Features:**

- Both DC and AC inputs
- Surge ratings of 2000W; Maximum bypass current of 10A
- 3 Stage Battery Charger
- AVR Function
- Compatible with GEL, AGM, Sealed Lead Acid, Flooded Lead Acid batteries.

Specification:

Model		CPS1000-121	CPS1000-122	CPS1000-241	CPS1000-242
Rated power		1000W			
Surge power		2000W (Few seconds)			
Inverter part	Input voltage	12V		24V	
	Output voltage	110V	230V	110V	230V
Charger part	Input voltage	90-120VAC		190-265VAC	
	Output voltage	12V		24V	
	Max. current	10A		5A	
Transfer time		15ms			
Output waveform		Pure Sine Wave			
Protection function		Bat. Low voltage alarm&shut down, over temperature, over voltage, short circuit, reverse polarity, earth leakage, overload			
Cooling fan		By load control			
AC input protection		AVR function			
Dimension		33*23*10cm (L*W*H)			
N.W/unit		3560g			
QTY/Ctn		2pcs			
Warranty		24 months			
Meas./Ctn		40*31.5*38cm			
Certification		CE-EMC/LVD, RoHS			
Packing		Gift box			
Packing list		1 * 1000W Power Inverter; 1 * User Manual; Spare fuse; DC connect cable*1 set			